
使用前需注意

★若有任何因体现液体掉进产品内部，请关闭电源，并经合格的专业技术人员检查后方可再行使用。
★本设备内有高压危险，不可自行维修，拆卸设备。
★当长机出现异常时，请立即停止使用，可尝试重新开关机或接插电源。
★请不要用湿手接插电源插头。
★请在正确的输入电压下使用本产品。
★设备应当连接到带保护接地的电网电源输出插座上。
★如果长时间不使用设备，请切除设备的电源插头。
★请勿将产品置于温度过高或过低（45°C以上/0°C以下）的环境中。
★请勿将产品放在热源附近，易受阳光直射，沙尘过多，潮湿，通风不良，易受振动，表面凹凸不平的地方，或者有窒息闭的车内。
★请勿将任何重物放在产品的上面，请勿将装有液体的物品放在产品的上面。

部件介绍





操作说明

● 开/关机
长按电源键 ● 为开关机

开机显示：
关机显示：

● 开/关仓
短按开/关仓键 ● 开关仓门

开仓显示：
关仓显示：

● 切换输入模式
长按MODE键 ● 切换CD IN模式/USB IN模式

CD IN模式显示：
USB IN模式显示：

● 切换输出模式
短按MODE键 ● 切换LO/DIGIT输出模式

LO模式显示：
DIGIT模式显示：

选择LO输出模式时，仅后板LO接口有输出，选择DIGIT输出模式时，后板AES、COAX、OPT接口有输出。

● CD播放
开机后，长按MODE键确认进入CD模式，随后开始读碟，显示：；如果没有碟片，显示""。
CD载入完成时，显示屏将显示CD总曲目以及碟片总时长。

● UAC播放
开机后，长按MODE键确认进入USB模式，将USB解码线插入侧面USB接口，连接手机或电脑进行解码。通过驱动识别到DP11，进行连接，识别成功后播放曲目，显示屏显示曲目格式及采样率。

(注：Windows系统电脑连接到台式解码模式DP11，空调需要前往官网下载USB DAC驱动，并按照相应的教程安装驱动后方可使用。
下载地址：https://www.fiio.com/Driver_Download_OSX系统无需安装此驱动)

● 抓轨
1.首先使用FAT32格式的U盘，插入后板USB口。
2.进入CD模式，长按播放/暂停键或按遥控器的REC键，进入抓轨。
主界面显示：
抓轨异常显示：

● 电源说明
台产品支持AC/DC供电，AC供电，接上电源线即可使用，如需DC供电，确保DC电源的输出电压为12V，输出电流≥2A。

● 播放顺序
短按播放顺序选择键 ● 可切换播放顺序，一共有四种播放顺序可选
顺序播放（主界面不显示）/单曲循环（主界面显示 ↻1）/列表循环（主界面显示 ↻）/随机播放（主界面显示 ⤮）

● USB设置
进入UAC模式，短按停止键 ● 可进行USB1.0/USB2.0切换。


遥控器说明



包装清单

● DP11 ● USB C转C数据线 ● 遥控器 ● 电源线 ● 快速入门 ● 售后维修卡

了解更多

● 有关产品的相关视频说明和常见问题解答（FAQ），请扫描产品 FAQ 二维码。
● 了解更多产品信息，请访问：www.fiio.com

产品名称：台式CD数字播放器
产品型号：FD211D
额定输入：AC 100-240V~
尺寸：约211x230x67mm（不含机脚垫）
重量：约1800g
执行标准：GB4943.1-2022
制造厂：广州飞傲电子科技有限公司
地址：广州市白云区龙归街富良良龙路21号

由于产品不断改进，各项规格及设计随时更改，恕不另行通知。

环保材料说明

产品中有害物质的名称及含量

部件名称	有害物质					
	铅(Pb)	汞(Hg)	镉(Cd)	六价铬(Cr(VI))	多溴联苯(PBB)	多溴二苯醚(PBDE)
PCB	X	O	O	O	O	O
PCBA 焊点	X	O	O	O	O	O
元器件	X	O	O	O	O	O
显示屏*	X	O	O	O	O	O
电池*	X	O	O	O	O	O
外观件	O	O	O	O	O	O
配件*	X	O	O	O	O	O

注：表中标记"*"的部件，按现业现有水平暂时无法实现有害物质的替代。
标"O"是该件表示出属在该部件所含的产品中无显部件，是含概有中这部件在是。
标"X"是该有害物质在该部件所有均质材料中的含量均在SJ/T 26572-2011规定的限量要求以下。
表示该有害物质至少在该部件的某一均质材料中的含量超出SJ/T 26572-2011规定的限量要求。


根据中国电子行业标准SJ/T 11364-2014 和相关的中国政府法规，本产品及其某些内部组件都含有上述指明有环保使用期限的标志。某些环境友好使用期限可能会因产品及其组件上的使用期限和设计实施有不同。超过上的使用期限标识优先于产品上任何与之相关的同样不同的环境使用期限标识。


此环保使用期限只适用于产品在规定的条件下工作

Precautions Before Use

★If any solid object or liquid falls into the product, please switch off the power immediately and have it checked by qualified professional personnel before further use.
★There are high-voltage risks inside the device. Please do not repair or disassemble the product on your own.
★In case of system errors, please stop using it immediately. You can try to turn the DP11 off and on, or unplug and replug the power cable.
★Please do not plug or unplug the power plug with wet hands.
★Please use this device under an appropriate input voltage.
★The device should be connected to the power outlet with grounding protection.
★If the device will not be used for a long period, please unplug the power cable.
★Please do not place the product in environments with excessively high or low temperatures (above 45°C or below 0°C).
★Please do not place the product near heat sources, in direct sunlight, in dusty areas, humid environments, rain-prone locations, places subject to mechanical shock, uneven surfaces, or inside a closed car.
★Please do not place heavy objects or items containing liquids on top of the product.

Parts Introduction





Operation Explained

● Power on/off
Long press the Power button ● for 3s to turn on/off the device.

When powered on, the screen displays: 
When powered off, the screen displays: 

● Open/Close tray
Short press the Open/Close tray button ● to open/close the tray.

When the tray is opened, the screen displays: 
When the tray is closed, the screen displays: 

● Input mode switching
Long press the MODE button ● to switch between CD IN/USB IN.

In CD IN mode, the screen displays: 
In USB IN mode, the screen displays:

● Output mode switching
Short press the MODE button ● to switch between LO/DIGIT.

In LO mode, the screen displays: 
In DIGIT mode, the screen displays: 

When LO output mode is selected, only the LO port on the rear panel will output audio. When DIGIT ouput mode is selected, AES, COAX, and OPT ports on the rear panel will output audio.

● CD playback
Turn on the DP11. Long press the MODE button to confirm and enter CD mode. Then the player will start disc reading and the screen will display: 
; If no disc is inserted, the screen will display "".
When CD loading is complete, the screen will display the number of tracks and total playback time.

● UAC playback
Turn on the DP11. Long press the MODE button to confirm and enter USB mode. Connect the USB decoding cable to the USB port on the side panel, then connect your phone or computer for decoding. The device will be recognized as "DP11". Once successfully recognized, the DP11 will play a track and the screen will display the track format and sampling rate.

(Note: You would need to install the USB DAC driver when connecting the DP11 to a Windows computer for USB decoding. Please download the USB DAC driver on our website https://www.fiio.com/Driver_Download and follow relevant instructions to install it. For macOS, it runs driver-free.)

● CD ripping
1. Insert a USB flash drive formatted in FAT32 into the USB port on the rear panel.
2. Switch to CD mode, then long press the Play/Pause button or press the REC button on the remote control to start CD ripping.

The screen will display: 
When a ripping error occurs, the screen will display: 

● Power supply
This product supports both AC and DC power supply. For AC power, simply connect the power cord to use the device. For DC power, please ensure the output voltage is 12V and the output current is ≥ 2A.

● Playback sequence
Short press the Playback mode selection button ● to switch between different playback modes. There are four playback modes in total: Sequential playback (not displayed on the screen)/Single track repeat (the screen shows ↻1)/Repeat all (the screen shows ↻)/ Shuffle playback (the screen shows ⤮).

● USB settings
In UAC mode, short press the Stop button ● to switch between USB1.0/ and USB2.0.

Remote control introduction

List of Items Included

● DP11 ● USB-C to USB-C data cable ● Remote control
● Power cord ● Quick start guide ● Warranty card

To learn more

● For related video instructions of the DP11 and FAQ (Frequently Asked Questions), please scan the QR code.
● To learn more about the product, please visit our website: www.fiio.com

Due to continuous improvement, every specification and design is subject to change at any time without further notice.

WEEE Directive & Product Disposal

At the end of its serviceable life, this product should not be handed as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

Hereby, Guangzhou FiiO Electronics Technology Co., Ltd. declares that this device is in compliance with Directive 2014/30/EU. The full text of the EU declaration of conformity is available at: www.fiio.com/doc

FCC NOTICE:
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
● Reorient or relocate the receiving antenna.
● Increase the separation between the equipment and receiver.
● Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
● Consult the dealer or an experienced radio/TV technician for help.
The equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. The equipment should be installed and operated with minimum distance 20 cm between the radiator & your body.
Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.