

50mm

60mm

## Smart Socket Instruction

### Parameters

- Product Name: Smart Breaker
- Model: RMC001
- Rated Voltage: 100V-240V AC 50HZ/60HZ Rated Current: 16A(Max)
- Material: PC
- Support System: Android & iOS

### Download & Registration

Scan the QR code to download "Smart Life" APP . You can also search "Smart Life" in either APP store or Google Play to install the APP.

Open the "Smart Life" APP, tap "Register" to register "Smart Life" account with your phone number or E- mail. Then sign in the APP.



### Add Devices in Easy Mode(Recommend)

Make sure your smart device is energized and your mobile phone is connected to your Wi-Fi router. Long press the power button for more than 5 seconds until the indicator light begin to flash quickly (2 times per second about), this means the device is already for configuration.

Open your "Smart Life"APP and tap "+" on the top right of the APP. Select Device Type, tap it and 'Confirm indicator light rapidly blink". It will automatically get the password of the Wi-Fi network that your mobile phone connects to. Then tap "Confirm" to connect to the device.

When appears "Successfully added 1 device", it means the connection is complete and your device will be listed in your APP list.

### Add Devices in AP Mode

If failed in Easy Mode, users could add devices in AP Mode. Long press the power button for more than 5 seconds until the indicator light flash quickly, then long press it for another 5 seconds until the indicator light flash slowly.

Tap "+" on the top right of the APP, Select Device Type. Then tap "AP Mode" on the top right, "Confirm indicator light slowly blink" and "Confirm". Tap "Connect now" to go to the WLAN Settings interface in you mobile phone and select the Wi-Fi network named "SmartLife\_XXXX" to connect it.

Return to the "Smart Life" APP, the connection will start automatically.

When appears "Successfully added 1 device", it means the connection is done.